

BIOS Settings for the Gigabyte GA-EX58-UD5 motherboard with F7 BIOS

MB Intelligent Tweaker (M.I.T.)

CPU Clock Ratio: [22x]

Standard CMOS Features:

Date: [set]

Time: [set]

Drive A: [None]

Floppy 3 Mode Support: [Disabled]

Halt On: [No Errors]

Advanced BIOS Features:

Hard Disk boot Priority: [set your boot drive as #1]

First Boot Device: [CDROM]

Second Boot Device: [Hard Disk]

Third Boot Device: [Disabled]

Boot Up Floppy Seek: [Disabled]

Boot Up Num-Lock: [On]

Password Check: [setup if desired]

HDD S.M.A.R.T. Capability: [Enabled]

Limit CPUID Max. to 3: [Disabled]

No-Execute Memory Protect: [Enabled]

Delay for HDD (Secs): [0]

Full Screen LOGO Show: [Disabled]

Init Display First: [PEG]

Integrated Peripherals:

SATA RAID/AHCI Mode: [AHCI]

SATA Port0-3 Native mode: [Enabled]

USB Controller: [Enabled]

USB 2.0 Controller: [Enabled]

USB Keyboard Function: [Enabled]

USB Mouse Function: [Enabled]

USB Storage Function: [Enabled]

Azalia Codec: [Enabled] * *Disable this if you are using a separate sound card*

Onboard H/W 1394: [Enabled]

Onboard H/W LAN1: [Enabled] * *Disable this if you are using a separate network card*

Onboard H/W LAN2: [Disabled] * *You can enable this if you want to use both NICs*

Green LAN: [Disabled]

>SMART LAN1: [Press Enter]

>SMART LAN2: [Press Enter]

Onboard LAN1 Boot ROM: [Disabled]

Onboard LAN2 Boot ROM: [Disabled]

Onboard SATA/IDE Device: [Enabled]

Onboard SATA/IDE Ctrl Mode: [AHCI]

>Smart Backup: [Disabled]

Power Management Setup:

ACPI Suspend Type: [S3(STR)]

USB Device Wake-Up From S3: [Enabled]

Soft-Off by PWR-BTTN: [Instant-Off]

PME Event Wake Up: [Disabled]

Power On by Ring: [Disabled]

Resume by Alarm: [Disabled]

HPET Support: [Enabled]

HPET Mode: [64-bit mode]

Power On By Mouse: [Disabled]

Power On By Keyboard: [Disabled]

AC Back Function: [Soft-Off]